

Quick Start Guide



Model: ZL600

Version: 1.0

Due to regular upgrades of systems and products, ZKTeco could not guarantee exact consistency between the actual product and the written information in this manual.

How to configure the lock to the **ZKBioHLMS** software?

Step 1: Installing ZKBioHLMS

- ① Search for "ZKBioHLMS" on the ZKTeco's website www.zkteco.eu and download the installation package and install it.
- ② After installing and logging-in successfully, fill out the hotel information on the **Room Management** option of the Hotel module, including **Hotel Info Setting**, **Room Type**, **Room**, etc.

Step 2: Configuring the SLG410 ZigBee gateway

Please refer the configuration processes in the **SLG410 QSG**.

Step 3: Installing the Reader's driver

On the **Room View** page, click **Driver Download** to install the driver.

Note: The driver installation may be interrupted by the system. Please ignore the warning and continue with installation to issue the card. The driver is safe to use.

Step 4: Issuing Default Net Card to connect the lock and gateway

- ① Open the **Hotel Info Setting** page, select **Default Net Card**, click **Default Net Card** to issue.
- ② Open **Device Management**, choose the gateway which customers want to connect and then enable.
- ③ Swipe the card issued on ZL600. The lock will beep twice with a blinking blue light. After a few seconds, it will beep twice with a blinking blue light again, indicating successful operation. If it beeps thrice with a blinking red light, it indicates a failed operation. Please try again by swiping the card.

Note: If the operation fails again, enable the gateway and swipe the card again.

Step 5: Editing the lock details on the software

- ① Open **Device management** -> **Lock Management**, the lock will appear on the page automatically.
- ② Click the lock name to edit the lock details. The customers can enter the **Lock Name** on the pop-up window and fill out the **Lock Name**, **Room Name**, and **Room Area** as required.
- ③ Choose the lock to enable. After a few seconds, refresh the page, and the icons of both **Enable** and **Status of the lock** will change to green. Now, the lock can be used with the software smoothly.

Note: If the icons do not change to green, please wait for a few seconds and refresh again.



¿Cómo configurar la cerradura en el software **ZKBioHLMS**?

Paso 1: Instalar ZKBioHLMS

- ① Busque "ZKBioHLMS" en el sitio web de ZKTeco www.zkteco.eu descargue el paquete de instalación e instálelo.

② Despues de instalar e iniciar sesión correctamente, complete la información del hotel en la opción **Gestión de Habitaciones** del módulo Hotel, incluida la **Configuración de Información del Hotel**, **Tipo de Habitación**, **Habitación**, etc.

Nota: Si los iconos no cambian a verde, espere unos segundos y vuelva a actualizar.

Paso 2: Configurar el Gateway ZigBee SLG410

Por favor de revisar el proceso de configuración en la Guía Rápida del **SLG410**.

Paso 3: Instalar el controlador (driver) del lector

En la página **Room View**, haga clic en **Driver Download** para instalar el controlador.

Nota: El sistema puede interrumpir la instalación del controlador. Ignore la advertencia y continúe con la instalación para enrolar las tarjetas. El controlador es seguro de usar.

Paso 4: Enrolar la tarjeta de red predeterminada para conectar la cerradura y el gateway

- ① Abra la página **Configuración de Información del Hotel**, seleccione **Tarjeta de Red Predeterminada** y haga clic en **Tarjeta de Red Predeterminada** para enrolar.
- ② Abra **Administración de Dispositivos**, elija el gateway que se desea conectar y luego habilite.
- ③ Deslice la tarjeta enrolada en la cerradura ZL600. La cerradura emitirá dos pitidos con una luz azul parpadeante. Despues de unos segundos, volverá a emitir dos pitidos con una luz azul parpadeante, lo que indica un funcionamiento correcto. Si emite tres pitidos con una luz roja parpadeante, indica una operación fallida. Vuelva a intentarlo deslizando de nuevo la tarjeta.

Nota: Si la operación falla nuevamente, habilite el gateway y deslice la tarjeta nuevamente.



ZKTeco Europe

www.zkteco.eu

Copyright © 2020 ZKTECO CO., LTD. All Rights Reserved.